

Modelo	Dimensiones			Potencia transmitida en H P		
	D-Eje Max	D-Maza	D-Max Acople	500 R.P.M	1,500 R.P.M	3,000 R.P.M
F-1	15	25	53	2	6	12
F-2	20	36	78	3	9	18
F-3	32	50	100	6	18	38
F-4	46	70	132	18	54	108
F-5	55	85	161	31	94	189
F-6	70	106	180	54	162	327
F-7	80	120	226	85	240	480
F-8	90	140	243	161	483	963
F-9	120	190	298	475	1425	2850